

A method for generating [electrical] electrically conducting [or] and/or semiconducting structures in two or three dimensions, a method for erasing the same structures and an electric field generator/modulator for use with the method for generating.

5

BACKGROUND OF THE INVENTION

The invention concerns a method for generating [electrical] electrically conducting [or] and/or semiconducting structures in two or three dimensions in a composite matrix[, wherein the]. The matrix comprises one or more materials provided in spatially separate and homogenous material structures[, wherein the materials]. The materials can undergo specific physical and/or chemical changes of state in response to the supply of energy [can undergo specific and/or chemical changes of state], which cause transition from an [electrical] electrically non-conducting state to an [electrical] electrically conducting [or] and/or semiconducting state or vice versa, or a change in the electrical conduction mode of the of the material[, and wherein each]. Each material structure is made in the form of a thin layer.

The invention also concerns a method for [erasing] globally [electrical] erasing electrically conducting [or] and/or semiconducting structures generated in two or three dimensions in a composite matrix[, wherein the]. The matrix comprises two or more [material] materials provided in spatially separate and homogenous material structures[, wherein the materials]. The materials can undergo specific physical and/or chemical changes of state in response to the supply of energy, [can undergo specific

and/or chemical changes of state] which cause transition from an [electrical] electrically non-conducting state to an [electrical] electrically conducting [or] and/or semiconducting state or vice versa, or a change in the electrical conduction mode of the of the material[, and wherein each]. Each material structure is made in the form of a thin layer.

Finally, the invention concerns an electric field generator/modulator (EFGM) for patterning and generating [electrical] electrically conducting [or] and/or semiconducting structures in two or three dimensions in a composite matrix[, wherein the]. The matrix comprises one or more materials [respectively] provided in one or more spatially separate and homogenous material structures, [wherein the]

respectively. The materials [in response to the supplied energy] can undergo specific physical and/or chemical changes of state in response to the supply of energy, which cause transition from an [electrical] electrically non-conducting state to an [electrical] electrically conducting [or] and/or semiconducting state [and] or vice versa, or a change in the electrical conduction mode of the of the material[, and wherein each]. Each material structure is made in the form of a thin layer.

More particularly the present invention concerns the fabrication of two-and three-dimensional isolating, resistive, conducting [or] and/or semiconducting patterns and structures for use in electronic circuits which most particularly consist of a single or several stacked layers of thin films.

The evolution of microelectronic technology shows a steady trend towards smaller dimensions and reduced costs of the devices. Well-substantiated predictions show that [the] performance is going to increase, while the price per unit or device will decrease. However, today's microelectronic technology is substantially based on crystalline silicon and shows an increasing tendency towards diminishing returns, mainly due to the inherent limitations associated with the complexity of ultra-high resolution lithography and increasing demands of the material processing. Extrapolations of the present technologies based on crystalline silicon [may hence] are not [be] expected to offer dramatic breakthroughs in [regard of] either performance or price [and future]. Future improvements shall require manufacturing plants and manufacturing equipment, which are extremely capital-intensive.

[Microelectronics] On the other hand, microelectronics based on thin-film technology [may on the other hand confidently be] are predicted to deliver [in the near future] products representing real breakthroughs in [regard of] both performance [as well as of] and price in the near future. The shift from crystalline inorganic semiconductors to microcrystalline, polycrystalline or amorphous inorganic or organic semiconductors will introduce entirely novel boundary conditions with regard to the production of microelectronics [and particularly by]. Particularly, the blanks [having] can have form factors, which make large areas possible, i. e., the substrates [may] can be large sheets instead of wafers cut from blanks of limited size, and great flexibility with regard to architectures[, something which will be]. These are essential factors in the expected development of tomorrow's electronic technology. In the present invention special emphasis will be placed on the use of organic materials due to the ease whereby they [may] can be processed [with basis in]. Additionally,

organic materials allow for the use of large areas and multilayer blanks with precisely controllable thickness, [as well as their] and provide vast potential for chemical tailoring of the desired material properties.

[Particularly before] Before the use of electronics based on amorphous materials can [fulfil] fulfill their expected potential, further developments in certain areas are required. In [the] recent years an effort has been made to improve the semiconducting properties of organic semiconducting thin-film materials[, which]. These improvements have [given] caused dramatic and rapid increase in [the] transistor performance [up] to a point where organic-based transistors [may] can now compete with transistors based on amorphous silicon (see for instance Y.-Y. Lin, D. J. Gundlach, S. F. Nelson and T. N. Jackson, "Pentacene-Based Organic Thin Film Transistors". IEEE Transactions on Electron Devices, August 1997). Other on-going projects will lead to coating processes for thin film in order to generate organic and amorphous silicon semiconductors at low temperatures [and] with compatibility to a broad range of organic and inorganic substrate materials. This has lead to the development of extremely [cheap] inexpensive electronic devices with large areas based on the use of high-volume manufacturing methods.

In spite of this development a wholly satisfactory solution [to how] is still lacking for adaptation of the fabrication technology [shall be adapted and made suitable for a] for low-cost flexible high-volume production of electrical connections in the thin-film structures forming the electronic circuits [is still lacking]. Currently thin-film devices are based on amorphous silicon manufactured with current paths and conductors patterned with traditional methods such as lithography and vacuum metallization. The latter method has [formerly] also been applied to circuits for demonstration of organic-based semiconductor thin-film devices (see for instance A. R. Brown & al. "Logic gates made from polymer transistors and their use of ring oscillators", Science 270: 972-974[(1995)], 1995).

Alternatively, screen printing with conducting "ink" has been used to make transistors on flexible polymer substrates (see for instance F. Garnier & al., "All-polymer field-effect transistor realized by printing techniques", Science 265: 1884-1886[(1994)], 1994). Even though lithography may provide high resolution, it is relatively complex and includes [typically] wet chemistry steps [which] that are undesirable in high-volume production of multilayer organic thin-film structures.

Screen printing with ink is also far from ideal, as it only provides low to moderate resolution [besides being a "wet" method.], and is a "wet" method.

[As examples of prior art such it is evident from available patent literature may also be mentioned US patent No. 5 043 251 (Sonnenschein & al.) which] U.S.

Patent No. 5,043,251 (Sonnenschein et al.) is an example of prior art that discloses a process for three-dimensional lithography of amorphous polymers for generating a momentary permanent pattern in a polymer material [and which]. The process

comprises steps for providing doped non-crystalline layers or films of a polymer in a stable amorphous state under humane operating conditions. [In manufacturing the

patterns the] The film is masked optically and is exposed through the mask to radiation with sufficient intensity to cause ablation of the exposed portions to

manufacture the patterns such that a distinct three-dimensional imprint is generated in the film. This process [has among other been proposed for use] is used in the

manufacture of [an] optical data storage [disk. Further it is from US patent No. 5 378

916 (Mantell) known a photo-sensitive] disks. Further, U.S. Patent No. 5,378,916

(Mantell) discloses a photosensitive device in the form of a single-crystal structure, wherein different portions of the structure may have different compositions.

[Particular] Particularly, the structure forms a two-dimensional array [and a]. A first photosensitive portion comprises a material, which generates electron-hole pairs when

it is exposed to light within a predetermined first wavelength range, while another photosensitive portion comprises a material which is adapted to generate electron-hole pairs when it is exposed to light within another wavelength range distinctively

different from the first wavelength range. [Yet further it is from US patent 5 677 041

(Samyling) known] Still further, U.S. Patent No.5,677,041 (Smayling) discloses a

transistor device [which] that is made by forming a doped layer of radiation-sensitive material on a substrate. The radiation-sensitive material may among others be polyimide, polymer, an organic dielectric, a conductor or a semiconductor. The

substrate [may] can be silicon, quartz, gallium arsenide, glass, ceramic, metal or polyamide. A neutral or undoped layer of another radiation sensitive material is

formed over the doped layer. First and second source/drain areas are then formed in the neutral layer and extend down to a top portion of the doped layer. A gate area is formed in the top portion of the neutral layer between the first source/drain area and the second source/drain area such that a channel area in the doped layer is provided under the gate area. Drain/source and gate electrodes [as] are formed by irradiation of

the uppermost neutral layer through a mask patterned in accordance with the desired electrode pattern and realized such that it intensity-modulates the radiation. In addition the mask may also be realized as a phase-shifting mask.

Finally [it is from], the article, "Polymeric integrated circuits and light-emitting diodes" of D. M. de Leeuw & al., IEDM, pp. 331-336 (1997) [known], discloses a [

]MISFET wholly realized in polymer [and with the use of]. The polymer materials [which] are given the desired electrical properties by [an] exposure to UV radiation. In the manufacture photochemical patterning of doped [electrical] electrically conducting polyaniline films, so-called PANI thin films is used. [The] After the films are dissolved in a suitable solution, [whereafter] a photo-initiator is added to the solution [which] that has been deposited on a suitable substrate, such as a polyimide film. [By thereafter] After exposing the PANI film to deep UV radiation through a mask, the initially conducting polyaniline is converted [in the exposed areas] to the non-conducting leucoemeraldine form[. The] in the exposed areas. Accordingly, the starting point [here] is [accordingly] a conducting polymer material[, the]. The area resistance of [which] the material is initially [is] 1 kilohm/square[, but which after]. After the exposure, the material obtains an area resistance of more than 10^{13} ohm/square. In this manner, dielectric structures [may] can be generated in an otherwise conducting matrix. Fig. 1 shows a MISFET according to Leeuw [&] et al. comprising a polyimide substrate 1 with a PANI thin film [which after]. After exposure to UV light through suitable masks [forms], isolating structures 6 are formed in the otherwise conducting thin-film material 3. The still conducting areas 3 in the PANI film define [respectively] the source and drain electrode of a MISFET transistor, respectively. Above the PANI film a further layer 4 is deposited in the form of a thin film of polythienylenevinylene or PTV [which] that is an organic semiconductor material. This layer 4 substantially determines the electrical parameters of the MISFET transistor. A film 5 of polyvinyl phenol PVP [which] that is opaque to UV radiation and visible light forms the gate isolator of the transistor and is [opaque to UV radiation and visible light is] deposited over the PTV film 4. [

]Another PANI film is [again] deposited on the top of the PTV film 5 and is patterned by radiation with UV light such that isolating structures 6 are formed. A still [electrical] electrically conducting area 2 forms the gate electrode of the MISFET structure.

If several transistors of [this] the kind [as] mentioned above [shall be] are combined in integrated circuits [realized] in the form of stacked film layers, vertical current paths [between for instance] must be used. For instance, vertical current paths can exist between source and drain electrodes in a transistor and the gate electrode in another transistor [must be used]. Such vertical current paths [may in principle] can be realized mechanically, for instance, by depositing a metal film over vertically etched steps in the structure. [Otherwise a close analogy is the use of] The throughplated holes in a circuit [boards] board for [realizing] forming a vertical connection between current paths on the upper and lower side of the circuit board are analogous to the vertical current paths.

SUMMARY OF THE INVENTION

An].

The main] object of the present invention is to provide improved [fabrication] methods [for] of fabricating conducting connections and electrodes in microelectronic components and [particularly] microelectronic devices with large areas on flexible substrates [by means of processes which combine]. The method further provides high-volume fabrication at low costs. Particularly, it is an object of the invention to provide [such] fabrication methods that [they may] can be used on layered physical devices, for instance [in the form of], three-dimensional circuit structures formed by a large number of adjacent stacked thin-film layers[, thus generating three-dimensional circuit structures. The present invention will thereby make possible flexible and cheap, but simultaneously also singularly]. Thus, the present invention provides flexible, inexpensive, simple and precise fabrication of devices such as flat display devices, logic circuits, memory devices [etc], and the like.

Further, it is also an object of the invention to provide a method for erasing such three-dimensional circuit structures in situ, such that the material in the structures is converted back to an initial virgin state [whereafter it]. After the erasing process, the material by means of a suitable method [may] can be reconfigured in the form of [electrical] electrically conducting [and] and/or semiconducting structures in three dimensions, [but] for instance with another pattern or another structure than the original.

the uppermost neutral layer through a mask patterned in accordance with the desired electrode pattern and realized such that it intensity-modulates the radiation. In addition the mask may also be realized as a phase-shifting mask.

Finally [it is from], the article, "Polymeric integrated circuits and light-emitting diodes" of D. M. de Leeuw & al., IEDM, pp. 331-336 (1997) [known], discloses a [

]MISFET wholly realized in polymer [and with the use of]. The polymer materials [which] are given the desired electrical properties by [an] exposure to UV radiation. In the manufacture photochemical patterning of doped [electrical] electrically conducting polyaniline films, so-called PANI thin films is used. [The] After the films are dissolved in a suitable solution, [whereafter] a photo-initiator is added to the solution [which] that has been deposited on a suitable substrate, such as a polyimide film. [By thereafter] After exposing the PANI film to deep UV radiation through a mask, the initially conducting polyaniline is converted [in the exposed areas] to the non-conducting leucoemeraldine form[. The] in the exposed areas. Accordingly, the starting point [here] is [accordingly] a conducting polymer material[, the]. The area resistance of [which] the material is initially [is] 1 kilohm/square[, but which after]. After the exposure, the material obtains an area resistance of more than 10^{13} ohm/square. In this manner, dielectric structures [may] can be generated in an otherwise conducting matrix. Fig. 1 shows a MISFET according to Leeuw [&] et al. comprising a polyimide substrate 1 with a PANI thin film [which after]. After exposure to UV light through suitable masks [forms], isolating structures 6 are formed in the otherwise conducting thin-film material 3. The still conducting areas 3 in the PANI film define [respectively] the source and drain electrode of a MISFET transistor, respectively. Above the PANI film a further layer 4 is deposited in the form of a thin film of polythiénylenevinylene or PTV [which] that is an organic semiconductor material. This layer 4 substantially determines the electrical parameters of the MISFET transistor. A film 5 of polyvinyl phenol PVP [which] that is opaque to UV radiation and visible light forms the gate isolator of the transistor and is [opaque to UV radiation and visible light is] deposited over the PTV film 4. [

]Another PANI film is [again] deposited on the top of the PTV film 5 and is patterned by radiation with UV light such that isolating structures 6 are formed. A still [electrical] electrically conducting area 2 forms the gate electrode of the MISFET structure.

If several transistors of [this] the kind [as] mentioned above [shall be] are combined in integrated circuits [realized] in the form of stacked film layers, vertical current paths [between for instance] must be used. For instance, vertical current paths can exist between source and drain electrodes in a transistor and the gate electrode in another transistor [must be used]. Such vertical current paths [may in principle] can be realized mechanically, for instance, by depositing a metal film over vertically etched steps in the structure. [Otherwise a close analogy is the use of] The throughplated holes in a circuit [boards] board for [realizing] forming a vertical connection between current paths on the upper and lower side of the circuit board are analogous to the vertical current paths.

SUMMARY OF THE INVENTION

An [.

The main] object of the present invention is to provide improved [fabrication] methods [for] of fabricating conducting connections and electrodes in microelectronic components and [particularly] microelectronic devices with large areas on flexible substrates [by means of processes which combine]. The method further provides high-volume fabrication at low costs. Particularly, it is an object of the invention to provide [such] fabrication methods that [they may] can be used on layered physical devices, for instance [in the form of], three-dimensional circuit structures formed by a large number of adjacent stacked thin-film layers[, thus generating three-dimensional circuit structures. The present invention will thereby make possible flexible and cheap, but simultaneously also singularly]. Thus, the present invention provides flexible, inexpensive, simple and precise fabrication of devices such as flat display devices, logic circuits, memory devices [etc], and the like.

Further, it is also an object of the invention to provide a method for erasing such three-dimensional circuit structures in situ, such that the material in the structures is converted back to an initial virgin state [whereafter it]. After the erasing process, the material by means of a suitable method [may] can be reconfigured in the form of [electrical] electrically conducting [and] and/or semiconducting structures in three dimensions, [but] for instance with another pattern or another structure than the original.

The above-mentioned features and advantages are realized according to the present invention with a method which is characterized by applying to [the] a separate layer an electric field with given field strength and/or characteristics adapted to the specific response of the material to the energy supplied by the field[, modulating in].

5 In each case the fields are modulated spatially according to a determined protocol which represents a predetermined pattern of [electrical] electrically conducting [or] and/or semiconducting structures in the relevant material structure[, whereby in the layers in]. In response to the energy supplied by the field two-dimensional [electrical] electrically conducting [or] and/or semiconducting structures are generated in the
10 layers with the pattern predetermined by the protocol[, and then optionally providing]. Then, two or more layers are optionally provided in a stacked configuration, such that the composite matrix formed by separate adjacent layers is provided with [electrical] electrically conducting [or] and/or semiconducting structures in three dimensions.

Further, it is [according to the invention] advantageous that the electric field is
15 modulated spatially in a plane substantially parallel with a layer by means of an electrode device with patterned electrodes[, the electrode device by]. By selective supply of voltage to the electrodes according to the determined protocol [generating], the electrode device generates electrical point or line potentials, which generate the [electrical] electrically conducting [or] and/or semiconducting structures.

[It is according to invention advantageous that the stacked configuration is formed by two or more layers] According to another aspect of the invention, after generating the [electrical] electrically conducting [or] and/or semiconducting structure in each layer [being], it is advantageous that two or more layers form a stacked configuration. Each layer is combined into laminated multilayer structures [which forms] that form the composite matrix with [electrical] electrically conducting [or] and/or semiconducting structures in three dimensions.

20 [It is according to] According to yet another aspect of the invention [also], it is advantageous to positioning the multilayer formed by a lamination of two or more self-supporting layers into a stacked configuration. [A layer is after] After the lamination to adjacent layers, a first layer is then preferably positioned such that two or more two-dimensional [electrical] electrically conducting [or] and/or
25 semiconducting structures in the first [-mentioned] layer according to the protocol register with one or more two-dimensional [electrical] electrically conducting [or] and/or semiconducting structures in adjacent layers[, whereby]. Thus, one or more

vertical [electrical] electrically conducting [or] and/or semiconducting channels are generated in the cross-direction through the layers.

Finally, it is according to the invention advantageous providing an [electrical] electrically conducting [or] and/or semiconducting structure which forms a vertical channel through the layer according to the protocol, in [electrical] electrically conducting [or] and/or semiconducting connection with one or more two-dimensional [electrical] electrically conducting [or] and/or semiconducting structures in this layer[, each]. Each channel preferably [being] is generated with a conductivity or conduction mode which is constant between the layers or with a conductivity or conduction mode which varies between the layers.

A method for global erasing according to the invention is characterized by applying globally to the composite matrix an electric field with given field strength and/or characteristics adapted to the specific response of the material to the energy supplied by the field until the materials in their entirety arrive in the electrically conducting and/or non-conducting state in the composite matrix in response to the energy supplied by the field [in their entirety arrive in the electrical or non-conducting state.].

[An] According to the another embodiment of the invention, an electric field generator/modulator [is according to the invention characterized in that it] comprises a first electrode means with a plurality of parallel strip electrodes provided in a plane[, a]. A second electrode means with a plurality of parallel strip electrodes is provided at a distance from the first electrode means and superpositioned thereto in a second plane parallel with the first plane such that the electrodes mutually are substantially orthogonally oriented in a matrix-like arrangement[, that the]. The electrode means [over cross-connection devices] are connected with a controllable power supply[, the electrical field generator/modulator in the] over cross-connection devices. The space between the electrode means [being] in the electrical field generator/modulator is adapted for receiving a thin-film material in the form of a discrete component or a continuous tape [which without touching the electrode means continuously or intermittently]. The thin film material is fed through the space without touching the electrode means continuously or intermittently, and with simultaneous positioning and alignment spaced apart from and between the electrode means in a plane substantially parallel thereto[, whereby the electrical]. The electrically conducting [or] and/or semiconducting structures can be generated according to a determined protocol [and]

by means of point, line or area potentials [is] created between selected electrodes in the electrode means when [the former] electrodes are supplied with electric power over the cross-connection devices [are supplied with electric power]. Preferably [are], the electrodes in each electrode means are provided on or in surfaces of respective
 5 substrates facing each other and/or [in that connection] preferably are made as a part of the substrates and form conducting structures in the substrate material.

Further it is according to the invention advantageous that the distance between the electrode means is controllable depending on the thickness of the thin-film material.

10 Finally, it is according to the invention advantageous that the electrodes in each electrode means are provided with a mutual distance between 0.1 μm and 1.0 μm and that the electrodes in each electrode means are formed with substantially constant width of 0.1 μm to 1.0 μm .

BRIEF DESCRIPTION OF THE DRAWINGS

15 The invention shall now be explained in more detail in connection with a survey of its basic principles and with the use of exemplary embodiments in connection with the appended drawings, wherein

fig. 1 shows a MISFET with the electrodes formed of photoconvertible material
 20 according to prior art[.];

fig. 2a, b schematically respectively in section and plan view an embodiment of the electric field generator/modulator (EFGM) according to the invention and its use in a first step in the method for generating according to the invention[.];

25 fig. 2c, d schematically in respectively section and plan view EFGM as shown in fig. 2a, b and used in a second step in the method for generating according to the invention[.];

30 fig. 2e, f schematically in respectively section and plan view EFGM as shown in fig. 2a, b and used in a third step of the method for generating according to the invention[.];

fig. 3 schematically the embodiment of the method for generating according to the invention, combined with a lamination of single layers into a multilayer structure[.];

fig. 4 a section through a multilayer structure with conducting [and] and/or semiconducting structures as generated by the steps shown in fig. 2a-f, fig. 5 a

5 schematic section through a laminated multilayer structure which comprises conducting or semiconducting structures generated by the method according to the present invention[.];

10 fig. 6 a schematic section through a diode structure generated by the method according to the present invention[.];

fig. 7 a schematic section through a MOSFET structure generated by the method according to the present invention[.];

fig. 8 a schematic section through a logic inverter structure based on the MOSFET structure in fig. 7 and generated by the method according to the present invention[.];

15 fig. 9 the equivalent diagram of an AND gate realized in CMOS technology[.];

figs.10a-d in plan view sublayers in an AND gate structure generated by the method according to the invention and according to the equivalent diagram in fig. 8 with the use of MOSFET structures as shown in fig. 7[.];

20 fig. 11 the AND gate structure in fig. 10 as a stacked multilayer configuration, but exploded in the separate sublayers; and[.];

fig. 12 schematically another variant of the AND gate structure in fig. 10 and with the separate MOSFET structures provided mutually connected in a vertical configuration.

DETAILED DESCRIPTION OF THE INVENTION

Now the basic principles of a method according to the present invention
25 whereby three-dimensional structures with a well-defined mode and degree of

electrical conduction are generated by spatially controlled patterning in situ in convertible materials (CM) [which have such]. The convertible materials have properties such that their electronic properties are converted reversibly or irreversibly under the effect of radiation, heat, or electric fields. The method for generating such structures according to the present invention is based on the use of electric fields, either direct current fields or alternating current fields. Initially the three-dimensional [electrical] electrically conducting [or] and/or semiconducting structures can be generated as two-dimensional structures [of this kind]. The as two-dimensional structures are generated by direct local influence of the electric field on a single layer [and appears as three-dimensional by joining]. Joining single layers into a multilayer structure forms three-dimensional structures. Typically an electric field-convertible material (EFCM) will be an organic material, for instance a molecule, an oligomer or a polymer where a phase transition from an initial first state to a new second state takes place upon being subjected to an electric field[, for instance] of a given field strength or with a given frequency.

As mentioned in the following, it is presupposed that the most important change taking place from the first to the second state, is the degree of electrical conduction. In the following, the method for generating and erasing [of electrical] electrically conducting [or] and/or semiconducting structures by means of electric fields shall be discussed both generally and more specifically in connection with a description of the figures.

For polymers such as polyaniline [there are] conduction ratios between two states are observed as high as 10^{10} , as shown in the above-mentioned paper by de Leeuw & al.[, observed conduction ratios between two states as high as 1010. In this case it concerned] This paper addressed in situ conversion of a single layer of irradiation convertible material from conducting to non-conducting state in order to generate electrical connections in a single electronic circuit. [Electrical] Electrically conducting connections in doped polyaniline films (PANI films) were defined by exposure to deep UV radiation through a patterned mask.

A multilayer stack of different electric field-convertible materials [may] can be provided on a substrate, which [may] can be flexible or rigid, and conducting or non-conducting. The field-convertible material [are] is made conducting, semi-conducting or isolating (i.e., non-conducting) in desired patterns by subjecting a number of single layer field-convertible materials to spatially-controlled electric

fields[, and with subsequent combination of]. Subsequently, the layers can be combined into a multilayer stack. Multilayer stacks of field-convertible material are of particular interest in connection with multilayer thin-film circuits where it is required to generate [electrical] electrically conducting lines, current paths,

5 connection points or electrodes in several layers such that the conducting structures in one layer has a precisely controlled spatial relationship to the conducting structures in the layers which are located above or below. One example is thin-film field effect transistors (TFET) where the source and drain electrode in a layer must be correctly positioned relative to the gate electrode₂ and [with] intervening isolating and

10 semiconducting layers. Another example is electrical connections between the layers where traditional solutions in many cases are unsatisfactory[, for]. For instance [by incorporating]₂ a number of steps such as forming open channels or vias between suitable points₂ which then shall be electrically connected in the different layers [and], can be incorporated with subsequent filling or casing of the channels with a

15 conducting material[, such as this finds its parallel in]. This is analogous to the use of through-plated holes in circuit boards to obtain a connection from the front to the back of the circuit board. [A third instance is the generation of] In another example, capacitors are formed by defining conducting areas₂ which are aligned mutually opposite in two layers separated by an isolating layer. [Evidently not only highly]

20 Highly conducting, [but also] isolating resistive and semiconducting patterns in multilayer structures are all aspects of the [greatest importance. Such as] present invention. As will be explained in more detail in the following, patterns of this kind [may] can be generated by using the method for generating [electrical] electrically conducting [or] and/or semiconducting structures or patterns according to the present

25 invention. [With regard to the precision and clarity the] The following description [shall, however. be introduced by emphasizing on] emphasizes how patterns and three-dimensional structures are defined, which [either] are [very] good or [very bad] poor electrical conductors [shall be defined].

Multilayer structures as described herein are of particular interest when they are integrated with thin-film semiconductors in order to form complete circuits. [The present standard] Conventional procedures for fabricating microelectronic circuits, which exploit the semiconducting properties of a common silicon substrate₂ restrict automatically the realizable architectures to the kind [which] that allows access to the substrate for all active devices. If the method according to the present invention is

used for generating [electrical] electrically conducting [or] and/or semiconducting structures in three dimensions by means of converted single stacked single layers, then whole devices [may] can be generated in [this manner] without any essential restriction with regard to the size or complexity [as] because scaling [quite] simply takes place by joining more layers to the stack. [As] Since each layer [may] can be made thin, for instance with an order of magnitude of 10-100 nm, the resulting volumetric density for the circuit patterns and hence the performance per weight or volume unit [may] can be extremely high. Further, hybrid architectures [may] can be realized with the use of layers which [includes] include electrical field-converted electronic structures which are formed on the top of and function in cooperation with traditional silicon-based electronic circuits.

[The basic] An object of the present invention is the generation of [electrical] electrically conducting, semiconducting or resistive structures in three dimensions within a multilayer material in monolithic format[, as the]. The structures [mentioned] are generated [with the use of] by electric fields in the form of point, line or area potentials. An embodiment of the method [for generating with the use of electric field shall now be] is now described with reference to figs. 2a-f.

Fig. 2a shows a section through an electric field generator/modulator according to the invention [which] that functions as an electric patterning device for electric field-convertible materials. The electric field generator/modulator is realized such that it both generates the field and [in addition also can modulate] modulates the fields spatially, [i. e.] i.e., in a plane or two-dimensions [and generate electrical], thereby generating electrically conducting [or] and/or semiconducting structures with the desired pattern in this plane. In the following [will hence], the electric field generator/modulator [abbreviated be] is denoted as EFGM. [EFGM 20 comprises as] As shown in fig. 2a in section and in fig. 2b in plan view, EFGM 20 comprises a first electrode means E1, consisting of thin parallel electrodes 21 and another electrode means E2 provided spaced apart from the electrode means E1 in a plane parallel thereto. The electrode means E2 consists similarly of thin parallel electrodes 22 provided such that they are oriented substantially orthogonal to the electrodes 21 in the electrode means E1. The electrode means E1, E2 are connected with a power supply 23[, here] shown as a direct voltage power supply[, but]. However, the power supply 23 may also be an alternating voltage power supply. The power supply 23 is connected with the electrode 21[;], 22 in the electrode means E1[;], E2 over

respective cross-connecting devices [21,24] 24, 25. The distance between the electrode means E1, E2 allows a thin film of electrical field-convertible material EFCM₂ in fig. 2a denoted as SS1₂ to be inserted between the electrode means E1, E2, without contacting these electrodes. The electrode means E1, E2 [may] can be

5 formed of self-supporting or supported thin films₂ wherein the electrodes 21,22 in each case are embedded in the film material. Similarly [it is to be understood that], the layer SS1 of the field-convertible material EFCM [may] can be a continuous tape [which] that is inserted in EFGM 20 between the electrode means E1, E2 in a substantially continuous movement. By applying voltage [e. g.], e.g., to an electrode

10 21 in the electrode means E1 and to an electrode 22 in the electrode means E2₂ an electric field perpendicular to the layer SS1 is formed in the intersection between the electrodes 21 and 22 [and the]. The field-convertible material SS1 [will be able to transfer] can transform from a non-conducting to a conducting state in areas [which is] that are influenced by the field between the electrodes [21,22] 21, 22. If an

15 electrode 21 and another electrode 22₂ respectively₂ are addressed electrically in this manner, an approximate point potential is obtained in the intersection between. [If e. g.] For example, if an electrode 21 in the electrode device E1 and all electrodes 22 in the electrode device E2 are addressed, a field is obtained substantially in the form of a line potential along the electrode 21 in question [and correspondingly].

20 Correspondingly, a line-like structure will be generated, for instance an [electrical] electrically conducting structure in the layer SS1 which is located between the electrode devices E1, E2 [will be generated]. If [an] a number of electrodes 21 [which] that are located juxtaposed to each other in the electrode device E1 and correspondingly a plurality of electrodes 22 which are juxtaposed to each other in the

25 electrode device E2, the field [which are] created between the electrode intersections [will generate] generates an area potential [and it may for]. For instance [be generated], an electric area structure can be generated in the layer SS1 by this field. In figs. 2a, 2b [such electrical], these electrically conducting structures are [e. g.] generated substantially as area structures[, but it is to be understood that there also

30 may be generated as point of line structures, dependent]. However, point or line structures can be generated depending on the manner whereby the electric field is generated.

Figs. 2c and 2d show respectively in section and plan view how EFGM 20 is used for generating [for instance electrical] electrically conducting structures 9 in a

second layer by addressing the electrode means E1, E2 in EFGM 20 in a suitable manner. Correspondingly, figs. 2e, f [also shows] show in section and plan view EFGM 20 with a third layer SS3 [which here for instance]. Layer SS3 is patterned with semiconducting structures 10. As shown in [fig] figs. 2a-f, the patterning of the field-convertible material EFCM takes place for each separate layer SS1, SS2, SS3. [but these layers may] However, as mentioned above[,], these layers can be present in the form of self-supporting single films of EFCM and assembled into a multilayer stack, [such this] which schematically is shown in fig. 3. The fabrication of circuits realized with [electrical] electrically conducting [and] and/or semiconducting structures in EFCM can take place with tapes of EFCM in continuous paths as shown. Each tape or each film [are], shown in fig. 3 [shown] as three films EFCM1, EFCM2[,], EFCM3 [and are], is converted by electric field to the desired spatial pattern in a separate EFGM 20 for each of the paths. Then [follows the assembly], the layers are assembled into a multilayer structure MLS, [e. g.] e.g., by gluing or heat-assisted lamination. The multilayer structure MLS [may well] can be provided on a substrate [which, of course,] that is not subjected to any electric field[, but]. However, the substrate is laminated to the multilayer structure MLS in the same process step. In each case a flexible tape MLS is obtained [which] that either [may] can be folded [or], coiled or cut into segments, for instance, to make single circuits. In fig. 3, the field-convertible material EFCM in the form of three tapes or films EFCM1, EFCM2, EFCM3 is drawn from respective rolls [R3] R_a and conveyed in separate lines by alignment rolls R_{b1}, R_{b2}, R_{b3}, R_{b4} in each line for tensioning and positioning of the tapes through EFGM 20. The completed patterned films EFCM1, EFCM2, EFCM3 are conveyed over a guide roll set [Re and possibly] R_c. Possibly after a further position adjustment [through], a lamination step R_d [and laminated] laminates the completed patterned films EFCM1, EFCM2, EFCM3 into the multilayer structure MLS. This multilayer structure [may as mentioned,] can include a substrate 1, which is drawn from a further roll R_a in a separate line[} and]. The substrate 1 is laminated together with the converted film material EFCM in the lamination step R_d. [For three] Three layers, which are laminated together in this manner and converted as shown in [fig] figs. [

[2a-f, [it may then as shown] can be represented schematically in section view as shown in fig. 4 [be obtained a]. A circuit structure [which] is thereby provided on the substrate 1. The conducting structures 9 and the semiconducting structures 10

contact each other vertically or extend horizontally in each of the layers SS1, SS2, SS3 as shown [and form together]. Together, the conducting structures 9 and the semiconducting structures 10 form three-dimensional structures [of this kind] in the desired pattern.

5 The electrode means E1, E2 in the electric field generator/modulator (EFGM 20)₂ as [for instance] shown in fig. 2a and fig. 2b, [may] can be formed in or on substrates of a non-conducting material [and the]. The electrodes 21, 22 [may then] can be provided on the opposite surfaces of the substrates or embedded in the substrates. They may also form conducting structures in the substrate material itself.

10 The electrode width and the mutual distance between the electrodes 21, 22 in each electrode means E1, E2 [will be determining] is determined for the spatial resolution in the patterning of the conducting or semiconducting structures and the achievable pitches. In compatibility with today's semiconductor technology₂ the electrodes 21, 22 [thus] can be realized with a width between 0.1 and 1.0 μm and corresponding
 15 mutual distances. It is [with present technology wholly possibly] possible to realize electrode widths, [e. g.] e.g., in thin films provided on substrates, of 0.1 μm or less by nanotechnology[, for instance] printing methods, or by means of chemical methods. The circuit patterns [which] that are realized with EFGM20 [with the method] according to the present invention [will] are at least [be] dimensionally compatible
 20 [with that which optimally may be] those achieved by using [for instance] microlithography in silicon-based circuit technology[. Dependent], for instance. Depending on the thickness of the thin film material wherein conducting or semiconducting structures[, i. e.] (i.e., circuit patterns[, shall be]) are generated, the distance between the electrode devices E1, [
 25]E2 can be controlled [in order] to achieve an optimum definition of the potentials formed between the electrodes. The control may take place via [not shown] micromechanical servocontrol means (not shown), which are well-known to persons skilled in the art. [-]During the generation of the circuit pattern₂ the space between the electrodes [may besides] can be filled with an isolating gas with high dielectric
 30 strength in order to prevent [break-down] breakdown between the electrodes.

The power supply 23 in EFGM 20[, e. g.] (e.g., as shown in fig. 2a and 2b[,]) may either be a direct current source or an alternating current source. Preferably [it will be realized as], power supply 23 is a controlled power supply and [be] able to


supply the electrode means E1, E2 with current with different modes and characteristics. For this purpose both the power supply 23 and the cross-connection means 24, 25 [hence will] can be connected with [a not shown] an external control device [which may](not shown) that can be programmed according to the protocol for a desired circuit pattern and corresponding control the generation of the desired [electrical] electrically conducting [or] and/or semiconducting structures in the layer material or the thin film material between the electrode means E1, E2. Protocols and required software [may] can be loaded to the [not shown] control device (not shown) from any external source [and it is hence nothing against that]. Therefore, the fabrication of circuits [with the use of] using EFGM 20 [may] and the above method can be managed from a distant locality.

[There shall now be given a more] A detailed discussion of the electric field-convertible materials EFCM [which may] that can be used in the method according to the present invention[, as well as] and specific techniques [which may] that can be used in [the] an embodiment of said method follows. The basic principle of in situ field-conversion of materials is to generate conducting or semiconducting structures by means of spatially modulated and/or field strength modulated electric fields. [The] Additionally, the conversion itself may [additionally] be reversible or irreversible. Concrete examples [of this will be given below. It must be mentioned that EFCMs at the time being] are provided below. EFCMs are in an early development stage [and it]. It is [to be] expected that ongoing research and development activities in [the] this field will dramatically [shall] increase the number of available materials.

[It is in] In the present invention, it is particularly preferred [using] to use EFCMs which by being subjected to an electric field remain in [this state] an altered state (e.g., conducting and/or semiconducting) until they again are subjected to a field which brings the material back to the initial state (e.g., non-conducting). This is [among other] the case of different organic macromolecules and other materials [which] that generally are known as molecular electronic materials. [An instance of a] A material of this kind is disclosed in the paper "A new material for optical, electrical and electronic thin film memories" by Z. Y. Hua & G. R. Chen, Vacuum, Vol. 43, No. 11: 1019-1023 (1992). This material is an organometallic charge-transfer complex M (TCNQ) formed by TCNQ [(7,7,8,8-tetracyanoquinodimethan, C₁₂H₄N₄)](7,7,8,8-tetracyanoquinodimethan, C₁₂H₄N₄) which functions as an electron acceptor molecule with different metals as electron-rich donors. The metals [may]

can be Li, Na, K, Ag, Cu or Fe. M (TCNQ) may [under] transfer from a high impedance state to a low impedance state in response to the application of electric fields [and for the sake of that also] or energy supplied in the form of heat or light radiation [transfer from a high impedance state to a low impedance state]. Generally

the reaction can be written as



The process is reversible, as the return reaction [may] can be obtained by supplying energy ε in the form of heat, electrical fields or photon radiation. [The] Because of the reversible reaction [results in that], M (TCNQ) [may] can be used for generating a bistable switching medium, [for instance] such as an erasable memory material. [In the method] Only electric fields are used in methods according to the present invention [only electric fields are used and not irradiation]. Irradiation is not used. In thin layers, for instance of 100-200 nm, M (TCNQ) has non-linear current-voltage characteristics, [something] which [may] can be used for realizing memories of the type ROM and RAM. [For this purpose it] It is of particular interest that M (TCNQ) stably and [reproducibly] reproducibly allows current-controlled bistable electrical switching. [In an electrical] For instance, in an electrically addressable memory [for instance], the high impedance state [may be used for representing] can represent binary 1 and the low impedance state binary 0. The transition time between two such states is less than 400 ns. [-] Further examples of relevant materials are discussed in W. Xu & al., "Two new all-organic complexes with electrical bistable states", Appl. Phys. Lett. 67: 2241-2242 (1995) and the [therein] appended literature references therein. The materials mentioned are bistable and have well-defined thresholds for conversion from conducting to [nonconducting] non-conducting state and vice versa with the use of electric fields.

In certain field-convertible materials, including TCNQ, the conversion from a non-conducting to a conducting state may also take place when the energy is supplied in the form of the heat. As the field-convertible material basically is dielectric or strongly resistive, an electric alternating field applied via the electrodes [which over the electrodes is applied] with a suitable frequency to the material[,] may induce heat in the potential area [and a]. The heating [with] causes a subsequent conversion of the material from a non-conducting to a conducting state in this area [may then take place]. The power supply [must] is then [be] operated as an alternating power supply

and the thermal conversion [must be] is regarded as a secondary effect induced by the electric field. In order to obtain good spatial definition of the generated [electrical] electrically conducting [or] and/or semiconducting structures, the thermal field [which is] induced by the alternating field in the material [must be] is precisely controlled.

5 The thermal field will [namely] propagate through the material and cause a temperature increase [which] that may influence the electrical properties of the material outside the potential area [which ideally shall define]. Ideally the potential area defines the spatial extent of the generated structure. If the field-convertible material is regarded as an infinite thin layer, the temperature increase [will make itself
10 felt unto] extends a distance from [for instance] a point potential which falls together with the intersection point of the activated electrodes, with a thermal diffusion length defined by the formula

$$\mu = (\kappa/\pi f p c)^{1/2} \quad (1)$$

where the material parameters

15 κ = thermal conductivity,

$f = 1/\tau$ the characteristic frequency which is \square the inverse of the pulse duration τ ,

p = the density of the material, and

c = the specific heat of the material.

It follows from equation 1 that in order to reduce the thermal diffusion and
20 obtain a sharp spatial definition of the desired [electrical] electrically conducting or semiconductor structures, an alternating current pulse should be used which provides high field strength and a fast temperature increase in the potential area with subsequent rapid conversion of the field-convertible material. This [may] can be achieved by combining a high field strength with high field frequency and with the
25 use of field-convertible materials in the form of thin films with a thickness of 100 nm [it is supposed that an]. Effectively, unwanted thermal diffusion [effectively] can be avoided by using alternating current pulses of at most a few microseconds. [In this connection the] The field characteristics [must] are also [be] tuned to the desired degree of conductivity on the potential areas, which ideally defines the generated
30 conducting [and] and/or semiconducting structures.

Electrical connections between different layers in thin-film materials or other types of electronic materials present a major challenge for the fabrication of microelectronics. Precise positioning of conducting paths in each layer plane and in the perpendicular direction to the planes is of paramount importance and comprises

typically forming vias or holes which [may] can be filled with conducting material in order to create connections perpendicular to the layers. The physical manufacture of the holes in the prior art takes place by means of drilling, punching or etching, and the conducting material is added by mechanical filling, electroplating, etc. Very clearly
 5 processes of this kind represent a significant complication and a substantial cost with an accompanying limited precision.

In the present invention the connections, as well as active and passive devices [may], can be generated in the same processing sequence which defines the [electrical] electrically conducting [and] and/or semiconducting structures in each
 10 layer, [i. e.] i.e., with the same kind of spatial precision as the structures themselves and without resorting to further and other types of manufacturing steps. Fig. 5 shows the basic principle for the particular case where a single conducting path 9 shall be generated between a portion of [for instance of] a conducting structure in a layer SS5 and a portion of another conducting structure 9 in a layer SS8 spaced apart from the
 15 former. By repeated conversion of a small area in the same location of [in] each of several adjacent layers between the termination points of a conducting or semiconducting structure, a column [9'of] 9' of conducting material is formed as shown in fig. 5 [and electrical]. Electrical conductivity is obtained stepwise from the starting layer SS5, which contains the first conducting structure, to the final layer SS8
 20 which contains the second conducting structure. The cross-section of column [9'may] 9' can be defined arbitrarily via the selected electric field pattern. A number of parallel conducting columns [may] can be generated by direct extension of this procedure [and the]. The columns [may] can begin and end in different layers, such [this is apparent from] as shown in fig. 5. In a given layer which contributes [with] a
 25 conducting structure 9 in connection with one or more conducting columns of vertical conducting structures 9', the latter shall be made concurrently with other conducting 9 or semiconducting structures 10 which are patterned in this layer, for instance, SS6 in fig. 5[, i. e.] (i.e., without having to carry out other or different processing steps). Typically the degree of conversion from a non-conducting to a conducting state or
 30 vice versa can be controlled by the field strength and/or its time characteristics, and possibly also by the duration of the field. Thus a column, which connects points in two different layers [may], can be formed such that it functions as a resistor in a circuit by choosing the degree of conductivity in segments from layer to layer along the column.

[A] Additionally, a method for erasing [electrical] electrically conducting [or] and/or semiconducting structures generated in three dimensions forms a part of the invention.

In principle [may electrical] electrically conducting [or] and/or semiconducting structures in single layers can be erased selectively with the use of EFGM20 as shown in any of the figs. 2a-f and suitable spectral modulation. [After] However, after joining [of] single layers into a multilayer structure MLS_2 , the erasing at time being can[, however,] only be performed globally [by the]. The multilayer structure, in case the matrix, is globally [is] subjected to an electric field with given field strength and/or characteristics and possibly adapted to the specific response of the material to the energy supplied by the field. The materials in the matrix will then be reconverted until the matrix in its entirety arrives in an [electrical] electrically non-conducting state[, something which will be]. This is the case if [it e. g.] the matrix is made of a material such as

M (TCNQ). A multilayer structure or matrix of M (MTCNQ) material may thereafter be reconfigured with new [electrical] electrically conducting [and] and/or semiconducting structure, but this is not [at present] possible by using electrical fields according to prior art techniques. However, [a] another method [for generating] can be used as disclosed by the simultaneously filed International Patent Application PCT/N099/00023 which belongs to the present applicant[, may be used.].

[As] According to the present invention, the method for generating [according to the present invention makes possible] provides that suitable materials [may] can be converted from an isolating to a semiconducting state or vice versa by electric fields, either directly or indirectly [(e. g.)(e.g., in the last instance due to a simultaneous local heating)], it will be]. It is possible to apply the method to manufacture [for instance] diodes and transistors [which may] that can be connected electrically with resistances and capacitors to form complete active electronic circuits. More specific examples of active components and circuits formed thereof shall be disclosed by the following examples.

Example 1

Fig. 6 shows a forward-biased pn junction diode with conducting and semiconducting structures generated [by the method] according to the invention and [realised] realized in thin-film technology with four sublayers SS1-SS4. The layers SS2 and SS3 contain

the active semiconducting material provided between the [electrodes] electrodes 11 in [respectively the] sublayers SS1 and SS4, respectively. The active material 10 in [the] sublayer SS2 is an n-doped semiconductor, while the adjacent active material [10'in the] 10' in sublayer SS3 is a p-doped semiconductor. [

5

]The electrodes 11 in the layers SS1 and SS4 are contacted by horizontal [electrical] electrically conducting structures or conducting paths 9 in the same layer. [The] Each separate layer in the diode structure [in] of fig. 6 [has] typically has a thickness of about 100 nm, such that the whole structure forms a multilayer structure with a

10 thickness less than 1 μm . The horizontal extension of the area of the diode structure will be determined by the spatial resolution [which is realized with the use of an EFGM, but with] of an EFGM. However, it is possible to form electrodes 21, 22 of the electrode means E1, E2, as shown in fig. 2a-f, [it will be possible to form electrodes 21,22] with pitches in the order of magnitude 0.2-1.0 μm [by]. These

15 electrodes can be formed using conventional lithographic methods or by using irradiation convertible materials and a method as disclosed in the above-mentioned international patent application PCT/N099/00023. Special printing methods or use of nanotechnological and chemical methods will [besides] be able to realize electrode structures [which] that are one order of magnitude smaller. Realistically [it may be

20 supposed that] with the available technologies for making the electrode devices it will be possible to modulate point and line potentials spatially in two dimensions to a smallest extension of 0.1 μm .

Example 2-MOSFET

Fig. 7 shows schematically a MOSFET for use in the present invention and

25 realized wholly in organic material in thin-film technology. The gate electrode 12 is provided in the sublayer SS1 and connected with a horizontal conducting structure 9, while the sublayer SS2 constitutes the gate isolator 13. The active semiconducting material 10 is provided in the sublayer SS3 and registers with the gate electrode 10. The source and drain electrodes 14 are provided in the following top layer SS4 and

30 are contacted by horizontal [electrical] electrically conducting structures 9 in the same layer. Each of the layers comprises either [electrical] electrically conducting structures or a semiconducting structure, as well as dielectric areas. The thickness of a MOSFET of this kind [may] can be $\frac{1}{2} \mu\text{m}$, while the extension in the horizontal

plane [such as may be realized with present technology will] can be from at most a few μm m to less than $1\ \mu\text{m}$, cf. what is said in example 1.

Example 3-Logic CMOS inverter

The MOSFET structure in fig. 7 may now be used in logic gates, for instance a logic inverter in CMOS technology as shown in fig. 8. An inverter of this kind is formed by parallel connection of the drain and source electrode in respectively an n-MOSFET and a p-MOSFET in a back-to-back configuration, with common gate electrode. For this purpose a vertical conducting structure 15 is generated and passes through all sublayers SS1-SS7 and connects the electrodes 14'. The output signal from the inverter is conveyed on this conducting structure 15 to a horizontal connecting structure 9 at left in the figure. The common gate electrode 12 of the MOSFET [receive] receives the input signal via the horizontal conducting structure 9 in the sublayer SS4 at right in the figure. The thickness of all sublayers [will then be] is less than $1\ \mu\text{m}$, typically realized with about a thickness of about $0.7\ \mu\text{m}$, while the horizontal extension of the inverter will have the same dimensions as stated above in connection with the discussion of the MOSFET structure in the figure 7.

Example 4-CMOS AND gate

Active components like the MOSFET structures shown in fig. 7 [may] can be used for forming integrated circuits by stacking [of] the sublayers with structures which have the desired electrical properties and wholly are realized in an organic thin-film technology. Specifically, the following example is [connected with] an AND gate realized in CMOS technology with the use of the transistor structure as shown in fig. 7. In order to facilitate the understanding of how active devices such as field-effect transistors [may] can be combined in multilayer structures and into functional devices [as], for instance logic gates, reference shall be made to fig. 9 [which]. Fig. 9 shows the circuit diagram for an AND gate realized in complementary MOS technology (CMOS technology). The CMOS AND gate is realized with [respectively] n-MOSFETS and p-MOSFETS of the enrichment type as switches, respectively. Two input signals A and B are conveyed respectively to the gate electrodes on p-MOS Q_1 and Q_2 and the gate electrodes on n-MOS Q_3 and Q_4 . If both input signals switches A and B are high, the output signal \bar{X} will be low. In this case Q_3 and Q_4 will both be

on and the p-MOS switches Q_1 and Q_2 will both off, [i. e.] i.e., no current flows and the output signal \bar{X} hence goes low. If, on the contrary, either the input signal A or the input signal B is low or both are low, [correspondingly] the p-MOS transistors Q_1 [respectively], Q_2 will be switched on and the output signal \bar{X} goes high, [as] because

5 either one or both of the serially connected n-MOS transistors Q_3 , Q_4 are off and no current flows. The devices Q_1 [, Q_2 , Q_3 , Q_4 realize[, as will be seen,] a NAND gate [and to]. To realize an AND gate it is necessary to connect the output of the NAND gate with a logical inverter which also is realized in [

10]CMOS technology[, respectively] with the use of a p-MOS switch Q_2 and an n-MOS Q_6 switch connected in parallel. This is a standard CMOS inverter [and if]. If its input signal \bar{X} is high, its output signal X [will be] is the [inverted] inverse of the input signal \bar{X} and hence low. Conversely a low input signal \bar{X} [will be] is inverted to a high output signal X [and this]. This corresponds to the input signals A and B to the NAND gate both being high. [In other words it is easily realized that circuit as

15 shown in fig. 9 realizes an AND gate and] Circuits such as the AND gate shown in fig. 9 can be realized with any number of inputs. Correspondingly, persons skilled in the art will understand that [correspondingly] logic OR and NOR gates [may] can easily be realized [and with any number of inputs. However, in]. In principle, all Boolean functions can be realized in combinations of one type of gate and one or

20 more inverters realized in CMOS technology, for instance, with the use of the transistor structure as shown in fig. 7.

[Purely practically the] The AND gate can be implemented in thin-film technology as shown in figs. 10a-10d and with the use of MOSFET structures corresponding to that shown in fig. 7. Figs. 10a-10d show the AND gate wholly

25 realized in thin-film technology [and] with the active and passive devices provided in four sublayers SS1, SS3-SS5. The first sublayer SS1 (fig. 10a) contains the gate electrodes g_1 - g_6 where the subscript points to the corresponding subscript for the MOSFETs Q_1 - Q_6 in fig. 9. The inputs A and B are conveyed to respectively the gate electrodes g_1 , g_3 and g_2 , g_4 and via horizontal conducting structures or current paths 9.

30 Correspondingly the gate electrodes g_5 , g_6 in the inverter are connected with a horizontal current path 9. A vertical [electrical] electrically conducting structure is denoted as 15[, the]. The symbol Δ [indicating] indicates that it extends upwards in vertical direction from the sublayers SS1. In fig. 10b₂ the symbols Δ and ∇ indicate

that the vertical conductor structure 15 in the layer SS3 extend vertically through this layer and on both sides thereof. The layer SS3 comprises areas with active semiconductor materials b_1 - b_6 (corresponding to 10 in fig. 7) which are assigned to and register with the corresponding gate electrodes g_1 - g_6 in the layer SS1. It is to be remarked that a layer SS2 [exclusively], apart from the vertical conductor structure 15 which also extends through this sublayer on both sides thereof, exclusively consists of dielectric material which forms a common gate isolator for the MOSFETs Q_1 - Q_6 which realize the AND gate. The layer SS2 is[, of course,] located between SS1 and SS3, but has been excluded from the drawing. The layer SS4 in fig. 10c is provided above and adjacent to the layer SS3 and comprises [respectively] the source electrodes [S1-S6] s_1 - s_6 and the drain electrodes d_1 - d_6 for the corresponding MOSFETs Q_1 - Q_6 , respectively. The active semiconductor material d_1 - d_6 [which] that is located in [the] layer SS3 is here indicated by stitched lines. The vertical current path 15 also extends also through the layer SS4 and to both sides thereof and contacts a horizontal current path 9 in the sublayer SS5 as shown in fig. [10d] 10d. This horizontal current path corresponds to the connection between the drain electrodes d_2 and d_3 for the corresponding MOSFETs Q_2 , Q_3 and is additionally also connected with the drain electrode d_1 on Q_1 . Another horizontal current path 9 realizes the serial connection between the source electrode [S3] s_3 on Q_3 and the drain electrode d_4 on Q_4 . The source electrodes [S4] s_4 and [S6] s_6 are grounded over further horizontal conductor structures 9, while the horizontal conducting structure 9 farthest to right in the layer SS5 is supplied with a voltage V_{dd} and connects the source electrodes [S1, S2, S5 on respectively] s_1 , s_2 , s_5 on Q_1 , Q_2 and Q_5 , respectively. A further horizontal current path 9 uppermost in fig. [10d] 10d forms the parallel connection between the drain electrodes d_5 , d_6 on Q_5 , Q_6 and the output line, denoted with X. The output signal \bar{X} from the NAND gate consisting of Q_1 , Q_2 , Q_3 , Q_4 is conveyed on the vertical current path 15. Fig. 11 shows schematically how the layers in fig. 10 appear in stacked configuration[, the]. The layer SS2 [with](i.e., the gate isolator [here being]) is included. [For] However, for the sake of clarity the stack[, however,] is shown exploded in its separate sublayers SS1-SS5[, but] with correct registration [and the]. The course of the vertical current path 15 through every sublayer is indicated by the stitched line. With the gate electrode layer SS1-SS5 provided on an underlying[, not shown] (not shown) dielectric layer, the total AND structure as shown in fig. 11

may have a thickness of $0.75\text{ }\mu\text{m}$ and an area of about $100\text{ }\mu\text{m}^2$ ($12\text{-}8\text{ }\mu\text{m}^2$). The volume of the structure will hence be about $75\text{ }\mu\text{m}^3$. With conservative spatial resolution this implies that about [10 000] 10,000 logic gates of this kind [may] can be realized on an area of 1 mm^2 and with a thickness well below $1\text{ }\mu\text{m}$. Correspondingly scaled, the length of the current paths 9,15 together [becomes] is $60\text{ }\mu\text{m}$.

Example 5-AND gate with vertically stacked CMOS circuits

A reduction of the current path length and a significant simplification of the structure of the AND gate [may] can be achieved by stacking the MOSFET structures vertically as shown in fig. 12. Again the same reference numbers as in figs. 10 and 11 are used[, and it will]. It can be seen that the vertical AND gate structure exploits the fact that the gate electrodes g_1 and g_3 of the transistors Q_1 , Q_3 are at the same common potential, the gate electrodes g_2 and g_4 in Q_2 , Q_4 on another common potential and the gate electrodes g_5 and g_5 in Q_6 on a third common potential. Hence the transistors Q_1 - Q_6 are [implemented] implemented as [

15] CMOS circuits in a pairwise back-to-back configuration by common gate electrode g_1 , g_3 ; g_2 , g_4 ; g_5 , g_6 for the corresponding MOSFET structures Q_1 , Q_3 ; Q_2 , Q_4 ; Q_5 - Q_6 . Each CMOS circuit is provided on an isolating layer, which in fig. 12 is located below Q_3 , between Q_1 and Q_4 and between Q_2 and Q_5 in each of the MOSFET structures. The gate electrodes g are also, of course, isolated from the active semiconductor material b [by], not explicitly denoted as isolating layers which

20 comprise the respective gate isolators. The horizontal current paths in figs. 10 and 11 are now substantially replaced by vertical current paths which extend through the layers and provide the same connection as shown in the equivalent circuit in fig. 9. Particularly the current path 15 is shown which also is realized vertically in the

25 configuration in fig. 10 and[, as will be seen,] as before connects the gate electrodes g_5 , g_6 on Q_5 , Q_6 with the connection between the drain electrodes d_2 , d_3 on Q_2 , Q_3 and the drain electrode d_1 on Q_1 ,

The vertical AND gate structure in fig. 12 including the substrate 1 is generated by a total of 24 sublayers, of which 6 relatively thick isolating layers form

30 the gate isolators and three corresponding thick isolating layers isolate the paired combinations of MOSFET structures mutually. With the same dimensions as indicated in connection with the description of fig. 11, the whole stacked layer configuration in fig. 12 [hence will have] has a thickness of about $3.0\text{ }\mu\text{m}$ and can be

provided on an area of $16 \mu\text{m}^2$. The total volume thus becomes less than $50 \mu\text{m}^3$, a reduction of the volume of 1/3 relative to the configuration in fig. 11. [Most] However, most important is, however, the reduction in the length of the current paths [which in]. In the configuration in fig. 11 from the indicated dimensions [will] the current paths have a length of $52 \mu\text{m}$, may in]. In the configuration in fig. 12 [well be], the current length is about $15 \mu\text{m}$ in an optimal embodiment, which implies a reduction of about 70%. [In this connection it shall particularly be taken in regard that] Note, fig. 12 is schematic and [that] the vertical current paths are mutually displaced in the horizontal plane in order to appear more clearly. They may, however, lie in the same plane, parallel to one of the side surfaces of the structure.

Within the scope of today's thin-film technology and using technologies as mentioned above in order to create [electrical] electrically conducting [and] and/or semiconducting structures in thin films by irradiation of convertible organic materials, it is wholly possible to reduce the linear dimensions in the horizontal direction, such that the component density [may] can be increased by at least one order of magnitude. This implies that the configuration in fig. 11 may realize about 10^5 logic gates of the kind shown on 1 mm^2 [and] with a layer thickness well below $1 \mu\text{m}$ [, while]. Additionally, the configuration in fig. 12 might realize about [6-105] $6 \cdot 10^5$ gates on the same area with a somewhat better form factor, such that the increase in the device density becomes about 33% relative to the device density of the configuration in fig. 11.

The processing of single layers[, i. e. the generating of electrical conducting and semiconducting structures may] (i.e., the generating of electrically conducting and/or semiconducting structures) may include possible post-treatments and corrections, e.g., a possible heat treatment before the separate layers are joined into a multilayer structure and form a stacked circuit configuration after the converting by means of electric fields has taken place and when it is performed as shown in figs. 2a-f and fig. 3[, include possible post-treatments and corrections, e. g. a possible heat treatment before the separate layers are joined into a multilayer structure and form a stacked circuit configuration.].

[For instance] For instance, after the conversion a heat treatment of single layers [after the conversion may] can be performed to control conducting or semiconducting properties, [e. g.] e.g., conversion of monomer to oligomer or polymer, doping, crystallization, etc. Such processes are well-known and have a wide

application [and]. Therefore, specific examples [shall hence not be given here. The] are not provided. For example, the heat treatment may [e. g.] be performed by means of irradiation. Another possibility is to use the electric alternating fields. In principle alternating fields may also be used to effect the field conversion of EFCM [and].

5 Then, the power supply 23 shown in figs. 2a-f [must then, of course, be] is an alternating voltage source. [In that connection it shall be remarked that a] A resistive material₂ which is subjected to an alternating field₂ will be heated. By using an alternating voltage field for generating a transition from a non-conducting to [for instance] a conducting and/or semiconducting state₂ a heating of the thus generated
10 [electrical] electrically conducting structure may take place and a possible desired heat treatment may also take place in situ and simultaneously with the conversion process.

[By for instance] For example, by using organic materials in the layers and generating the [electrical] electrically conducting [and] and/or semiconducting
15 structures with conversion [and] by means of electric fields according to the present invention, [it may be obtained] a far simpler and [cheaper] less expensive manufacturing of electronic devices is obtained than [which] is possible with today's inorganic semiconductor technology. If a reel-to-reel arrangement is used in the manufacture of circuits as shown in fig. [7,] 3, the production [may] can take place
20 with high volume and high speed and without essential dimensional limitations. With the joining of separate layers into a multilayer structure and forming of a stacked configuration, the registration between the layers will[, however,] be critical [among other] in order to ensure that vertical conducting structures in separate layers register mutually [and that for instance electrodes]. Electrodes and active semiconductor
25 materials in the semiconductor structures [do the same] also need to register mutually. The requirement for registration accuracy [will be] is given by the pitch [which may] that can be realized in the manufacture of the [electrical] electrically conducting [and] and/or semiconducting structures, but may practically also be realized by using interferometric methods for control and positioning, optically recordable marking, or
30 mechanical or electrical nanotechnology. Such measures, however, fall outside the scope of the present invention and are hence not discussed in greater detail, but must be regarded as known to persons skilled in the art.

By using the method for generation according to the present invention₂ the protocol for a given circuit configuration in multilayer design [may] can be generated

far from the manufacturing location of the circuit [and transmitted thereto]. For
example, the protocol can be transmitted to the manufacturing location for
downloading to [for instance] a control device [which] that controls the generation of
the physical circuit patterns in situ at the manufacturing location. [A] Thus, a user
5 [may hence thereby] can generate and produce circuits by tele-processing according
to the user's own specifications solely by transmitting the necessary instructions and
information. [The] Thereby, the present invention [may thus furnish] furnishes the
concept application-and customer-specific circuit production with a radically new
content.

10

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203